

Smartvest Wireless Button

Art.-Nr. FUBE35020A

Seite 1 von 2



The Smartvest Wireless Button lets you control various Smartvest Wireless Alarm System actuators, such as the Wireless Socket, the Wireless Door Bell or even self-configured scenarios, within the system. The Wireless Button can be mounted using the click-mount for walls supplied, so that the button can be easily removed for mobile use. Alternatively it can be mounted using adhesive mounting. Two different actions can be triggered by assigning the action a short or long press. If the battery is low, this is transmitted to the alarm panel.

Technologies

- Smartvest extension for controlling Smartvest actuators, i.e. Wireless Socket, Wireless Door Bell or self-configured scenarios
- Comes with a click-mount for walls, from which the button can be easily removed for mobile use. Alternatively it can be mounted using adhesive mounting.
- Individual configuration is possible for two actions (short/long press)
- Visual feedback via orange LED when starting up and in use
- Low battery notification sent to the Smartvest alarm control panel

Technical data - Smartvest Wireless Button

| | |
|-----------------------------|-----------------------------|
| Battery - battery operation | Yes |
| Battery - max. battery life | 1,5 y |
| Battery - quantity | 1 |
| Battery - type | CR2032 (3V) |
| Colour | White |
| Compatible with Secvest | No |
| Compatible with Smartvest | Yes |
| Dimensions | (B x L x H) 30 x 17 x 70 mm |
| Display | LED |

Smartvest Wireless Button

Art.-Nr. FUBE35020A

Seite 2 von 2

Technical data - Smartvest Wireless Button

| | |
|----------------------------|--|
| Gross weight | 0,058 kg |
| Housing material | Plastic |
| Max. humidity | 80 % |
| Max. operating temperature | 40 °C |
| Min. humidity | 10 |
| Min. operating temperature | -10 °C |
| Net weight | 0,028 kg |
| Power consumption | 0,014 mA |
| Radio frequency | 868 MHz |
| Radio modulation | FSK |
| Standby power consumption | 0,0086 mA |
| Tamper protection | No |
| Transmission power | 4,5 dBm |
| Wireless range | (Depending on installation) 30 - 100 m |